SS61 Datasheet

1μA Ultra low Iq, 0.8V Startup,1A Synchronous Boost

昇生微电子版权所有

SiNH MiCRO
昇生微电子

REVISION 1.0

2021-09-03

SS61

1μA Ultra low Iq, 0.8V Startup,1A Synchronous Boost

FEATURES

- Ultra low IQ when No Switching :1uA for adjustable version
- 0.8V Startup
- 5V/0.4A Output Capability at Vin=3V
- Output to Input Reversed Current Protection
- Up to 94% Efficiency
- Internal Synchronous Rectifier and Output Disconnect
- Short-circuit Protection
- Adjustable version and Fixed voltage version
- SOT23-6

APPLICATIONS

- Tablet, MID
- Smart Phone
- Power Bank

昇生微电子版权所有

责任及版权申明

Copyright© 2020~2030 by Sinhmicro Electronics Co. Ltd.

Parameters of the products of Sinhmicro Electronics may vary from model to model or as a result of other factors. This document cannot be deemed as any express or implied warranty or authorization.

Products of Sinhmicro Electronics are all sold according to the terms and conditions of sales provided at the time of purchase order confirmation. Customer shall obtain the latest relevant information from Sinhmicro Electronics before placing an order and verify that the information is complete and up to date.

Sinhmicro Electronics will provide technical support for customer's application assistance or product design, but Customer shall be solely responsible for the products and applications. To minimize the risks associated with customer's products and applications, customer shall provide adequate verification in terms of design and operation safety.

Customer acknowledges and agrees that, while any application-related information or support may still be provided by Sinhmicro Electronics, customer is solely responsible for satisfying all applicable laws, regulations and safety requirements related to its own products and the use of the products of Sinhmicro Electronics in its applications. Customer represents and agrees that it has all the expertise and knowledges required for developing and implementing safety measures, is able to predict the dangerous consequences of failures, monitor failures and their results, reduce the probability of failures that may cause personal injury and take appropriate corrective measures; Sinhmicro Electronics is not responsible for the loss not attributable to the defects of the products of Sinhmicro Electronics.

When customer is reselling the products of Sinhmicro Electronics, if its statement concerning the parameters of the products of Sinhmicro Electronics is different or false compared to the parameters stated by Sinhmicro Electronics, customer will lose all express or implied authorization in connection with the products of Sinhmicro Electronics. This is illegal and fraudulent commercial behavior; therefore, Sinhmicro Electronics will not assume any responsibility or obligation for such false statement.

Sinhmicro Electronics owns the copyrights and other intellectual property rights of all contents (including but not limited to products and services) developed by it or jointly developed with its cooperative companies, which are protected by law.

Without the written approval of our company, no entity or individual shall, in any way or for any reason, use, copy, modify, transcribe, disseminate any part of the above-mentioned products, services, information and materials, or use and sell them together with other products.

目录

SS61 DATASHEET 0

1 DESCRIPTION 4

2 TYPICAL APPLICATION 5

3 ORDERING INFORMATION 6

4 PIN CONFIGURATION 7

5 APPLICATION INFORMATION 8

5.1 LOOP OPERATION 8
5.2 ULTRA LOW CURRENT CONSUMPTION AT LIGHT LOAD OPERATION 8
5.3 SHORT-CIRCUIT PROTECTION 8
5.4 ADJUSTABLE OUTPUT VOLTAGE SETTING WITH FB PIN 8

6 ELECTRICAL CHACRACTERISTICS 9

6.1 ABSOLUTE MAXIMUM RATINGS 9
6.2 ELECTRICAL CHACRACTERISTICS 9
6.3 TYPICAL CHARACTERISTICS 10
6.4 TYPICAL CHARACTERISTICS CONT'D 11

7 PCB GUIDELINES 12

8 PACKAGE OUTLINE 13

9 HISTORY 14

昇生微电子版权所有

1 DESCRIPTION

SS61 is a high efficiency synchronous step-up converter with ultra- low quiescent current down to 1μA. It is capable of delivering at least 2W of power from a low voltage source, i.e. 0.4A at 5V output. It also features a true-shutoff function that disconnects the input from output, during shutdown and output short-circuit conditions. This eliminates the need for an external MOSFET and its control circuitry to disconnect the input from output and provides robust output overload protection. A switching frequency of 1.4MHz minimizes solution footprint by allowing the use of tiny and low profile inductors and ceramic capacitors. An internal synchronous MOSFET provides highest efficiency and with a current mode control that is internally compensated, external parts count is reduced to minimal. With the ultra-low Iq feature, SS61 is ideal for solution that requires low standby power and compact board size such as IoT applications.

SS61 is housed in a SOT23-6.

昇生微电子版权所有

2 TYPICAL APPLICATION




Figure 2-1 Typical application circuit

*Pin number is just for SOT23-6 package,adjustable version

*For fixed voltage version,R1,R2 and 22pF are not needed and pin5 is NC.

昇生微电子版权

3 ORDERING INFORMATION

Table 3-1 Ordering information

PART No.	Version	PACKAGE	TOP MARK	Pcs/Reel
SS61	Adjustable	SOT23-6	SS61	3000

昇生微电子版权所有

4 PIN CONFIGURATION




Figure 4-1 Pin configuration

Table 4-1 Pin configuration

SOT23-6 PIN	NAME	DESCRIPTION
1	OUT	Output pin. Bypass with a 4.7μF or larger ceramic capacitor closely between this pin and GND
2	GND	Ground Pin
3	EN	Enable pin for the IC. Drive this pin high to enable the part, low to disable.
4	IN	Input Supply Voltage. Bypass with a 4.7μF ceramic capacitor to GND
5	FB	Feedback Input. Add an external resistor divider from the OUT to FB and GND to set VOUT for adjustable output voltage. There is no FB pin for fixed voltage version. The pin is “Not Connected ”.
6	SW	Inductor Connection. Connect an inductor Between SW and the regulator output.

昇生微电子版权所有

5 APPLICATION INFORMATION

5.1 Loop Operation

SS61 is a high efficiency synchronous step-up converter with ultra-low quiescent current down to 1μA. It integrates a 250mΩLow Side Main MOSFET and 160mΩsynchronous MOSFET. It uses a PWM current-mode control scheme. An error amplifier integrates error between the FB signal and the internal reference voltage. The output of the integrator is then compared to the sum of a current-sense signal and the slope compensation ramp. This operation generates a PWM signal that modulates the duty cycle of the power MOSFETs to achieve regulation for output voltage.

The peak current of the NMOS switch is also sensed to limit the maximum current flowing through the switch and the inductor. The typical peak current limit is set to 1A. An internal temperature sensor prevents the device from getting overheated in case of excessive power dissipation.

5.2 Ultra low current consumption at Light Load Operation

Traditionally, a fixed constant frequency PWM DC/DC regulator always switches even when the output load is small. When energy is shuffling back and forth through the power MOSFETs, power is lost due to the finite RDSONs of the MOSFETs and parasitic capacitances. At light load, this loss is prominent and efficiency is therefore very low. SS61 employs a proprietary control scheme that improves efficiency in this situation by enabling the device into a power saving mode during light load and the no load quiescent current can be as low as 1μA.

5.3 Short-Circuit Protection

Unlike most step-up converters, the SS61 allows for short circuits on the output. In the event of a short circuit, the device first turns off the NMOS when the sensed current reaches the current limit. When OUT drops below IN, the device then enters a linear charge period with the current limited same as with the start-up period. In addition, the thermal shutdown circuits disable switching if the die temperature rises above 155°C.

5.4 Adjustable Output Voltage Setting with FB pin

By adding a resistor divider at FB pin (R1 and R2 as shown in the circuit below), SS61 can be set to any voltage level less than 5V at output node. The R2 is recommended to be 2Mohm or less, which will add about 0.5uA or more at output. The output voltage is set by following equation:

$$Vout=（R1+R2）/R2 \times 1.11V$$

6 ELECTRICAL CHACRACTERISTICS

6.1 ABSOLUTE MAXIMUM RATINGS

Table 6-1 Absoulute Maximum Ratings

PARAMETER	RANGE/VAULE	
IN OUT, SW, FB, EN Voltage	-0.3V~ 6.5V	
SW to ground current	Internally limited	
Operating Temperature Range	－40°C to 85°C	
Storage Temperature Range	－55°C to 150°C	
Thermal Resistance SOT23-6	θ JA	θJC
	180 °C/W	90°C/W
Lead Temperature (Soldering 10ssec)	260C	
ESD HBM (Human Body Mode)	2KV	
ESD MM (Machine Mode)	200V	

(Note: Exceeding these limits may damage the device. Exposure to absolute maximum rating conditions for long periods may affect device reliability.)

6.2 ELECTRICAL CHACRACTERISTICS

Table 6-2 Electrical Chacracteristics


PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
Quiescent Current at OUT, adjustable version	V_{EN}=V_{IN}, No load, Not switching		1	2	μA
Quiescent Current at OUT, fixed voltage version	V_{EN}=V_{IN}, No load, Not switching		1.2	2.5	μA
Quiescent Current at IN, fixed 3.3V version	V_{EN}=V_{IN}=3.6V		15	30	uA
Shutdown Supply Current at IN	V_{EN} =GND		0.32		μA
IN Startup Voltage	I_{OUT}=1mA， Hysteresis=200mV		0.75		V
IN Operation Voltage	After Start-up	0.55		5	V
Output Voltage at 5V		4.85	5	5.15	V
Output Voltage at 3.3V		3.2	3.3	3.4	V
Feedback Voltage		1.076	1.11	1.144	V
Switching Frequency			1.4		MHz
NMOS Switch On Resistance	I_{SW}=100mA		250		mΩ
PMOS Switch On Resistance	I_{SW}=100mA		160		mΩ
SW Leakage Current	V_{OUT}=5.2V, V_{EN}=GND, V_{SW}=5.2V or V_{SW}= 0V		10		μA
NMOS Switch Current Limit			1		A
Start-up Current Limit			1		A
Short Circuit Hiccup time	ON		1.3		ms


	OFF	33			ms
EN Input Current	VEN=5V or 0V	-1	0	1	μA
EN High Voltage	VOUT=5V	0.75			V
EN low Voltage	VOUT=5V	0.25			V
Thermal Shutdown	Rising, Hysteresis=25°C	155			°C


(VIN=3.6V, VOUT = 5V, unless otherwise specified. Typical values are at TA = 25°C.)


6.3 TYPICAL CHARACTERISTICS

(Typical values are at TA = 25oC unless otherwise specified.)













6.4 TYPICAL CHARACTERISTICS cont'd

(Typical values are at TA = 25oC unless otherwise specified.)









昇生微电子

7 PCB GUIDELINES





Figure 7-1 PCB layout example for SOT23-6 package

昇生微电子

8 PACKAGE OUTLINE

Package: SOT23-6



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	1.050	1.250	0.041	0.049
A1	0.000	0.100	0.000	0.004
A2	1.050	1.150	0.041	0.045
b	0.300	0.500	0.012	0.020
c	0.100	0.200	0.004	0.008
D	2.820	3.020	0.111	0.119
E	1.500	1.700	0.059	0.067
E1	2.650	2.950	0.104	0.116
e	0.950(BSC)		0.037(BSC)	
e1	1.800	2.000	0.071	0.079
L	0.300	0.600	0.012	0.024
θ	0°	8°	0°	8°

昇生微电子版权所有

9 HISTORY

Date	Version	Modification Record
2021/09/03	V1.0	Publish the first version

昇生微电子版权所有